



AUTO/MANUAL CONTROL CHASSIS

630-6055-XXX

FEATURES

Automata's AMC panel is used when the field technician requires outputs at the MINI Controller site while maintaining and/or testing the control system. The panel allows field personnel to select control outputs that are normally controlled by the central computer, and to disable controls for safety when providing maintenance to equipment. A red LED illuminates to give a visual indication of which the operator selects controls "on" manually, or when they are automatically selected "on" by the computer. A 2" pipe mount as well as a wall mount is included. When ordered with Automata's Field Stations or Field Controllers a harness is provided between them and the AMC Chassis. The devices controlled, i.e. valves, pumps, etc, are wired directly to the AMC Chassis relays. AMC panels are available for control of 4, 8, 12, 18, 20, or 24 outputs. The standard 6"x6"x6" enclosure has insertion slots for .05, 2 and 4Amp solid-state relay boards. The front panel includes cabling and plugs to connect to the FC or MINI Field Controllers. Power is supplied from either the Automata FC or MINI Field Controller.



Specifications			
AMC		04 Controls and LED	
AMC		08 Controls and LED	
AMC		12 Controls and LED	
AMC		16 Controls and LED	
AMC		20 Controls and LED	
AMC		24 controls and LED	
Options			
REL280-.5A-1	one-280VAC .5Amp	REL280-4A-1	one 24-280VAC 4Amp
REL280-.5A-4	four-280VAC .5Amp	REL280-4A-2	two 24-280VAC 4Amp
REL280-.5A-6	six-280VAC .5Amp	REL280-4A-3	three 24-280VAC 4Amp
REL280-.5A-8	eight-280VAC .5Amp	REL280-4A-4	four 24-280VAC 4Amp
		REL280-4A-5	five 24-280VAC 4Amp
		REL280-4A-6	six 24-280VAC 4Amp
REL280-2A-1	one-280VAC 2Amp	REL280-4A-7	seven 24-280VAC 4Amp
REL280-2A-4	four-280VAC 2Amp	REL280-4A-8	eight 24-280VAC 4Amp
The AMC is available with one of the following panels. Lockable NEMA-4 enclosure without sunshield Or AMC panel installed inside the Field Station's enclosure			

Email: sales@automata-inc.com • <http://www.automata-inc.com>
 Fax: (530) 478-5881 • Phone: (530) 478-5882 • (800) 994-0380
 138 New Mohawk Rd., Suite 151 • Nevada City, CA 95959-3248